


Zero-ohm Strap Resistors



DIMENSIONS in millimeters



FEATURES

- Resistive element made with high stability film allowing low end resistance and high current through resistance.
- Color band marking for ease of identification after mounting
- · Compatible with automatic insertion equipment

APPLICATIONS

• Electronic circuits for any usage

SERIES	A max.	Ø B max.	Øс	d
SL3	3.9	1.8	0.5	5.08
SL4	6.2	2.5	0.6	7.62

MECHANICAL SPECIFICATIONS

SL4	SL3
10 m Ω	15 m Ω
3 A	2 A
> 500 Vcc	> 500 Vcc
$\geq 10^5\mathrm{M}\Omega$	$\geq 10^5 M\Omega$
0.25 g	0.15 g
	10 mΩ 3 A > 500 Vcc $\geq 10^5$ MΩ

IDENTIFICATION

Brown body with a black ring in the middle.

PACKAGING

Reel of 5000 pieces: code B0 5000

"Ammopack" box of 1000 pieces: code AM 1000

Reel packaging as per CEI 286 and EIA 296D specifications

ORDERING INFORMATION					
SL	4	0U	AM 1000	e3	
SERIES	VERSION	OHMIC VALUE	PACKAGING	LEAD (Pb)-FREE	

SAP PART NUMBERING GUIDELINES						
SL	4	R00	A22			
SERIES	VERSION	OHMIC VALUE	PACKAGING			

Legal Disclaimer Notice



Vishay

Notice

Specifications of the products displayed herein are subject to change without notice. Vishay Intertechnology, Inc., or anyone on its behalf, assumes no responsibility or liability for any errors or inaccuracies.

Information contained herein is intended to provide a product description only. No license, express or implied, by estoppel or otherwise, to any intellectual property rights is granted by this document. Except as provided in Vishay's terms and conditions of sale for such products, Vishay assumes no liability whatsoever, and disclaims any express or implied warranty, relating to sale and/or use of Vishay products including liability or warranties relating to fitness for a particular purpose, merchantability, or infringement of any patent, copyright, or other intellectual property right.

The products shown herein are not designed for use in medical, life-saving, or life-sustaining applications. Customers using or selling these products for use in such applications do so at their own risk and agree to fully indemnify Vishay for any damages resulting from such improper use or sale.

www.vishay.com Revision: 08-Apr-05